





M.2 to mPCIe Convertor Board Compatibility List

2013Dec13 Gerry Chen

Brand / Model	Function	Interface	Size	M2MP1	M2MP1-E	M2MU2	M2MS1	Note
Intel 7260NGW	802.11ac, BT4.0	PCIe/USB key A/E	2230	Pass	Pass	NG	NG	WiFi Bluetooth combo card
Qualcomm Atheros QCNFA222	802.11n, BT4.0	PCIe/USB key E	2230	NG	Pass	NG	NG	WiFi Bluetooth combo card
Intel XMM7160	LTE	USB key B	3042	NG	NG	Pass	NG	
Huawei ME936	LTE, Europe	USB key B	3042	NG	NG	Pass	NG	
Huawei ME906V	LTE, America	USB key B	3042	NG	NG	Pass	NG	
Huawei ME906J	LTE, Japan	USB key B	3042	NG	NG	Pass	NG	
Huawei ME906E	LTE, Europe	USB key B	3042	NG	NG	Pass	NG	
Huawei MU736	HSPA+	USB key B	3042	NG	NG	Pass	NG	
SierraWireless 7355	LTE, America	USB key B	3042	NG	NG	Pass	NG	
SierraWireless 7305	LTE, Europe	USB key B	3042	NG	NG	Pass	NG	
SierraWireless 7330	LTE, Japan	USB key B	3042	NG	NG	Pass	NG	
Telit LN930	LTE	USB key B	3042	NG	NG	Pass	NG	
Telit HN930	HSPA+	USB key B	3042	NG	NG	Pass	NG	
BPLUS M2EM	SSD	SATA key B/M	2242	NG	NG	NG	Pass	
ADATA AXNS341N-64GM-B	SSD	SATA key B/M	2242	NG	NG	NG	Pass	
Sandisk X110	SSD	SATA key B/M	2242	NG	NG	NG	Pass	
Samsung MZNTD128HAGM	SSD	SATA key B/M	2280	NG	NG	NG	Pass**	** recommend add P16SF adapter for 2280 size
Intel SSD Pro 1500 Series	SSD	SATA key B/M	2280 2242	NG	NG	NG	Pass**	** recommend add P16SF adapter for 2280 size
Intel SSD 530 Series	SSD	SATA key B/M	2280	NG	NG	NG	Pass**	** recommend add P16SF adapter for 2280 size
Tohsiba THNSNHGDNT	SSD	SATA key B/M	2280	NG	NG	NG	Pass**	** recommend add P16SF adapter for 2280 size
LITE-ON L8T-128L6G-HP	SSD	SATA key B/M	2280	NG	NG	NG	Pass**	** recommend add P16SF adapter for 2280 size
Brand	Function	Interface	Size	M2MP1 Key A	M2MP1-E Key E	M2MU2 Key B	M2MS1 Key B/B+M	Note

<p>M2MP1 (M.2 Key A) for Wi-Fi, Bluetooth functions</p>  <p>M.2 Key A for Wi-Fi, Bluetooth</p> <p>mPCIe</p>	<p>M2MP1-E (M.2 Key E) for Wi-Fi, Bluetooth functions</p>  <p>M.2 Key E for Wi-Fi, Bluetooth</p> <p>mPCIe</p>	<p>M2MU2 (M.2 Key B) for CDMA, LTE, GPS functions</p>  <p>M.2 Key B for CDMA, LTE, GPS</p> <p>mPCIe</p>	<p>M2MS1 (M.2 Key B/B+M) for SATA-based Module</p>  <p>M.2 Key B/B+M for SATA-based Module</p> <p>mSATA</p>
------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------	---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------